

The right power supplies

Do you know our Electronic Products?

Before installing or using an electrical product, it is important to make sure you have the proper power supply. Connection to the wrong power supply could damage the product beyond repair. There is a suitable power supply for every electrical Locinox product.



	VOLTAGE	OPERATING CURRENT	POWER CONSUMPTION	IP RATING	AC-TRANS-12V-25W	DC-ACCESS-12V-20W	DC-POWER-12V-20W	DC-POWER-24V-25W	POWERSTONE	VENUS
B-MAG	12V DC 24V DC	460mA (12V) or 230mA (24V)	5.5W	68		✓	✓	✓	✓	✓
ELECTRADROP-E/-E-P	24V DC	1.04 A (normal) 2.3 A (peak)	25 W (normal) (Standby: 0,2 W) 55 W (peak) (Standby: 0,2 W)	66					✓	
ELECTRADROP-R/-R-P	24V DC	1.04 A (normal) 2.3 A (peak)	25 W (normal) (Standby: 0,2 W) 55 W (peak) (Standby: 0,2 W)	66					✓	
GATESWITCH	12V DC	0.8 A (LED)	10W (LED)	54		✓	✓			
INTRALEC	12V AC/DC 24V AC/DC	0,8A (12V) 0,4A (24V)	9,6W	54	✓	✓	✓	✓	✓	✓
LEKQU4	12V AC/DC	0,3 A	3,6W	54	✓	✓	✓			
LIKQU2	12V AC/DC	0,3 A	3,6W	54	✓	✓	✓			
MAG	12V DC 24V DC	MAG3000: 500 mA (12 V) or 250 mA (24 V) MAG6000: 460 mA (12 V) or 230 mA (24 V)	MAG 3000: 6W MAG 6000: 5.5W	68		✓	✓	✓	✓	✓
MAGMAG	12V DC 24V DC	MAGMAG3000: 500 mA (12 V) or 250 mA (24 V) MAGMAG6000: 460 mA (12 V) or 230 mA (24 V)	MAGMAG 3000: 6W MAGMAG 6000: 5.5W	68		✓	✓	✓	✓	✓
MAGUNIT-2500	12V DC 24V DC	460mA (12V) or 230mA (24V)	5.5W	68		✓	✓	✓	✓	✓
MODULEC-SA	12V AC/DC 24V AC/DC	1,25A (12V) 0,62A (24V)	15W	54	✓	✓	✓	✓	✓	✓
MODULEC-SF	12V AC/DC 24V AC/DC	1,25A (12V) 0,62A (24V)	15 W	54	✓	✓	✓	✓	✓	✓
MODULEC-SH	12V AC/DC 24V AC/DC	1,25A (12V) 0,62A (24V)	15W	54	✓	✓	✓	✓	✓	✓
SE	12V AC/DC	Emissa 1A Ruptura 1,5A	Emissa 12W Ruptura 18W	54	✓	✓	✓			
SEH	12V AC/DC	Emissa 1A Ruptura 1,5A	Emissa 12W Ruptura 18W	54	✓	✓	✓			
SLIMSTONE-X	24V DC Locibus	520mA (with heating)	1,5 W (> 5°C) + 12 W at max heating (< -25°C)	68					✓	
SLIMSTONE-2	10V-26V AC/DC	1.0A (with heating)	1,5W (> 5°C) + 12W at max heating (< -25°C)	68	✓	✓	✓	✓	✓	✓
S-MAG	12V DC 24V DC	460mA (12V) or 230mA (24V)	5.5W	68		✓	✓	✓	✓	✓
TRICONE	12V AC/DC	80 mA	1W	54	✓	✓	✓			

	VOLTAGE	POWER
AC-TRANS-12V-25W	Primary voltage: 230V AC / Secondary voltage: 12V AC	25W
DC-ACCESS-12V-20W	Primary voltage: 230V AC / Secondary voltage: 12V DC	20W
DC-POWER-12V-20W	Primary voltage: 230V AC / Secondary voltage: 12V and 13V DC	20W
DC-POWER-24V-25W	Primary voltage: 230V AC / Secondary voltage: 24V and 25V DC	25W
POWERSTONE	Primary voltage: 110V-240V AC / Secondary voltage: 24V DC	60W
VENUS	Primary voltage: 110V-240V AC / Secondary voltage: 24V DC	48W